

MLFB-Ordering data

6SL3210-5BE22-2UV0



Client order no. : Order no. : Offer no. : Remarks :

Item no. :
Consignment no. :
Project :

Rated data		General tech. specifications		
Input		Power factor λ	0.72	
Number of phases	3 AC	Offset factor $\cos \phi$	0.95	
Line voltage	380 480 V -15 % +10 %	Efficiency η	0.98	
Line frequency	47 63 Hz	Filter class (integrated)	Unfiltered	
Output		Ambient conditions		
Number of phases	3 AC	Cooling	External fan	
Rated voltage	400 V	Installation altitude	1000 m (3281 ft)	
Rated power (HO)	2.20 kW / 3.00 hp		1000 11 (3201 10)	
Rated power (LO)	2.20 kW / 3.00 hp	Ambient temperature Operation	10 (0.%) (14 140.%)	
Rated current (HO)	5.60 A		-10 60 °C (14 140 °F)	
Rated current (LO)	5.60 A	Storage	-40 70 °C (-40 158 °F)	
Rated current (HO) at 480V	4.80 A	Relative humidity		
Rated current (LO) at 480V	4.80 A	Max. operation	95 %	
Pulse frequency	4.00 kHz	Comm	unication	
Output frequency	0 550 Hz	Communication	USS, Modbus RTU	
		Sta	ndards	
		Compliance with standards	CE, cULus, C-Tick (RCM), KC	
		CE marking	EN 61800-5-1 /EN 60204-1 and EN 61800-3	

Overload capability

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s



MLFB-Ordering data

6SL3210-5BE22-2UV0



Figure similar

Mechanical data		Connections					
Mounting position	Wall mour	nting / side-by-side mounting	Max. n	notor cable length			
		Shielded		10 m (33 ft)			
Degree of protection	IP20 / UL c	JL open type		Unshielded		50 m (164 ft)	
Size	FSA		Converter losses to IEC61800-9-2*		300-9-2*		
Net weight	1.00 kg (2	2.20 lb)	Efficier	ncy class			
Width	90.0 mm	(3.54 in)				IE2	
Height	166.0 mm	n (6.54 in)	Comparison with the reference converter (90% / 31.00 (100%)		31.00 %		
Depth	145.5 mm	ı (5.73 in)	I	↑			
Inputs / outputs		100% ·	68.3 W (1.80 %)	75.2 W (1.90 %)	86.6 W (2.20 %)		
tandard digital inputs			1				
Number		4	50% -	54.2 W (1.40 %)	57.1 W (1.50 %)	61.2 W (1.60 %)	
Digital outputs			50 %	48.4 W (1.30 %)	50 W (1.30 %)		
Number as relay changeover	contact	1	25% -	•	-		
Number as transistor		1	The perce	entage values show the losse	i 50% es in relation to the rated appa	90% f	
analog inputs							
Number		2 (Can be used as additional digital input)	The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torqu generating current (I) over the relative motor stator frequency(f). The values are valid for the bas version of the converter without options/components.				
Analog outputs			*convert	ed values			
Number		1					