

MLFB-Ordering data

6SL3210-5BE23-0UV0



Figure similar

Client order no. :
Order no. :
Offer no. :
Remarks :

Item no. :
Consignment no. :
Project :

Rated	data	General tech. specifications		
Input		Power factor λ	0.72	
Number of phases	3 AC	Offset factor $\cos \phi$	0.95	
Line voltage	380 480 V -15 % +10 %	Efficiency η	0.98	
Line frequency	47 63 Hz	Filter class (integrated)	Unfiltered	
Output		Ambient conditions		
Number of phases	3 AC	Casling	External fan	
Rated voltage	400 V	Cooling		
Rated power (HO)	3.00 kW / 4.00 hp	Installation altitude	1000 m (3281 ft)	
Rated power (LO)	3.00 kW / 4.00 hp	Ambient temperature		
Rated current (HO)	7.30 A	Operation	-10 60 °C (14 140 °F)	
Rated current (LO)	7.30 A	Storage	-40 70 °C (-40 158 °F)	
Rated current (HO) at 480V	7.30 A	Relative humidity		
Rated current (LO) at 480V	7.30 A	Max. operation	95 %	
Pulse frequency	4.00 kHz	Communication		
Output frequency	0 550 Hz	Communication	USS, Modbus RTU	
		Standards		
		Compliance with standards	CE, cULus, C-Tick (RCM), KC	
		CE marking	EN 61800-5-1 /EN 60204-1 and EN 61800-3	

Overload capability

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s



MLFB-Ordering data

6SL3210-5BE23-0UV0



Figure similar

Mechanical data		Connections				
Mounting position	Through-hole mounting / wall mounting / side-by-side mounting		Max. motor cable length			
Degree of protection	IP20 / UL open type		Shielded Unshielded		25 m (82 ft) 50 m (164 ft)	
Size	FSB		Converter losses to IEC61			
Net weight	1.60 kg ((3.53 lb)				500-5-2
Width	140.0 m	m (5.51 in)	Efficiency class			IE2
Height	160.0 m	m (6.30 in)	Comparison with the reference converter (90% / 33.4 100%)		33.40 %	
Depth	164.5 m	m (6.48 in)	ŀ	↑		
Inp	outs / out	puts	100% -	85.0 W (1.70 %)	95.7 W (1.90 %)	O ^{114.0 W (2.20 %)}
Standard digital inputs			1			
Number		4	50% -	68.0 W (1.30 %)	72.3 W (1.40 %)	78.8 W (1.60 %)
Digital outputs			50%	60.8 W (1.20 %)	63 W (1.20 %)	
Number as relay changeove	er contact	1	25% -	•	•••••	
Number as transistor		1	_		50%	90% f
Analog inputs			The perce	entage values show the losse	es in relation to the rated appa	rent power of the converter.
Number		2 (Can be used as additional digital input)	The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.			
Analog outputs			*converte	ed values		
Number		1				