

# **MLFB-Ordering data**

6SL3210-5BE24-0UV0



Figure similar

Client order no. :
Order no. :
Offer no. :
Remarks :

Item no. :
Consignment no. :
Project :

Rated	data	General tech. specifications		
Input		Power factor $\lambda$	0.72	
Number of phases	3 AC	Offset factor $\cos \phi$	0.95	
Line voltage	380 480 V -15 % +10 %	Efficiency η	0.98	
Line frequency	47 63 Hz	Filter class (integrated)	Unfiltered	
Output		Ambient conditions		
Number of phases	3 AC			
Rated voltage	400 V	Cooling	External fan	
Rated power (HO)	4.00 kW / 5.00 hp	Installation altitude	1000 m (3281 ft)	
Rated power (LO)	4.00 kW / 5.00 hp	Ambient temperature		
Rated current (HO)	8.80 A	Operation	-10 60 °C (14 140 °F)	
		Storage	-40 70 °C (-40 158 °F)	
Rated current (LO)	8.80 A	Relative humidity		
Rated current (HO) at 480V	8.20 A	Max. operation	95 %	
Rated current (LO) at 480V	8.20 A			
Pulse frequency	4.00 kHz	Communication		
Output frequency	0 550 Hz	Communication	USS, Modbus RTU	
		Standards		
		Compliance with standards	CE, cULus, C-Tick (RCM), KC	
		CE marking	EN 61800-5-1 /EN 60204-1 and EN 61800-3	

### **Overload capability**

#### Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

### High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s



# **MLFB-Ordering data**

6SL3210-5BE24-0UV0



Figure similar

Mechanical data		Connections					
Mounting position	Mounting position Through-hole mounting / wall mounting / side-by-side mounting		Max. motor cable length				
Degree of protection			Shielded		25 m (82 ft)		
Size	FSB	FSB				50 m (164 ft)	
Net weight	1.60 kg ( 3	8.53 lb )		Converter losses to IEC61800-9-2		300-9-2^	
Width	140.0 mm	( 5.51 in )	Efficiency classIE2Comparison with the reference converter (90% / 100%)32.90 %			IE2	
Height	160.0 mm	( 6.30 in )			32.90 %		
Depth	164.5 mm	( 6.48 in )	I	↑			
Inputs / outputs		100% -	102.0 W (1.70 %)	112.0 W (1.80 %)	•• •		
Standard digital inputs			]				
Number		4	50% -	80.4 W (1.30 %)	85.0 W (1.40 %)	91.1 W (1.50 %)	
Digital outputs			50/0	71.5 W (1.20 %)	74 W (1.20 %)		
Number as relay changeove	r contact	1	25% -	•	<b>•</b>		
Number as transistor		1	_	ł	50%	90% f	
Analog inputs			The perc	entage values show the los	ses in relation to the rated appa	rent power of the converter.	
Number		2 (Can be used as additional digital input)	The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.				
Analog outputs			*converted values				
Number		1					